

# MI-1

## Using the CD200 Rally Timer at a manned Regularity Start (RS)

### 1. BASIC INSTRUCTIONS

The car will draw up and request to start on the next whole minute.

Write the requested time on the competitor's timecard and your checksheet.

Wait until less than 30 seconds to go and then connect and hold the Memory Chip on the top of the competitor's timecard onto the Timer. The Timer will beep once and display the start time for 2 or 3 seconds. The LED will start flashing red.

The Timer beeps again at 10 seconds to go, then beeps for a countdown from 5 seconds. At zero, a long beep sounds and the LED changes from red to green. Call out the countdown to the crew.

That's it. The car can go.



### 3. BEWARE - THINGS TO WATCH OUT FOR

You cannot transfer the start time from the Timer to the Chip when there is less than 10 seconds to go.

If you need to abort the start and hold the competitor back until the next minute, the Chip can be re-presented to the Timer and the previous data will be overwritten. You must also change the timecard and checksheet.

Your Timer is pre-programmed for the function of your control and the control number and should only be used again for a subsequent control if specifically instructed. The number in the top right corner of the display (i.e. 04) is the control sequence number. Pressing the 'Esc' button should show 'St 0:30' on the display to confirm the correct functional mode for a RS control is set up.

If for any reason you cannot transfer the time to the competitor's Chip, write an 'X' in the 'LT' column on the timecard and the Results will ignore the Chip time and take the time from the timecard. Also make a note of that on your checksheet.